

MODEL: R5K PUSH FOR HELP / STAFF REGISTRATION STATION



R4KSAR



FEATURES

- Two (2) call points with Call-Assurance LEDs and Monitor LED
- Push for Help and Staff Registration
- Back-lit pushbuttons for easy activation
- Cancel button
- Continuous supervision of station
- Plug-in connectors for easy service
- Optional antimicrobial Bio-seal to cover buttons and allow for easy disinfecting of the station

SPECIFICATIONS

Power Required: 7mA @ 15VDC

Power Required when used with Speaker Module:
 10mA @ 15VDC

Weight: 0.22 lbs (0.09 kg)

Size: **W:** 3.2" (8.1 cm)
H: 4.25" (10.8 cm)

D: 0.6" (1.5 cm) in back box: 0.5" (1.3 cm) off-wall

Backbox Requirement: 1-gang, Non-gangable [W: 2.25" (5.7 cm) H: 4" (10.2 cm) D: 3.5" (8.9 cm)]

Backbox Requirement when used with Speaker

Module: 3-gang, Non-gangable [W: 5.5" (14 cm) H: 3.75" (9.5 cm) D: 3.5" (8.9 cm)]

Housing and Finish: High-impact molded Cyclooy 2950 UL 94-5VB; light grey faceplate

Controls: Two (2) Push button for call actuation, One (1) Call-assurance LED, One (1) Call-assurance /Monitor LED, and One (1) Cancel button

Terminations: Plug-on connectors

Certification: Designed for compliance to ANSI/UL 1069, IEC 60950, CE, RoHS / WEEE Compliant. Assembled in a U.S. FDA Registered facility.

DESCRIPTION

The Responder® 5000 Push for Help / Staff Registration Station is an emergency dual pushbutton station that has the ability to place two (2) unique call priorities from a single station. The bottom button is used to place a "Staff Presence" or "Staff Registration" call. The Cancel button allows for cancellation of the call at the station. This type of station is normally located at a resident room head wall for placing a call for help, staff assist, and/or staff registration.

The Push for Help / Staff Registration Station is connected to its associated corridor light and is continually supervised

for station presence. Through programming, a "Trouble" message can annunciate at the associated consoles(s) when the station is removed from the system.